arXiv:1207.0563v1 [cs.SY] 3 Jul 2012

KRON REDUCTION OF GENERALIZED ELECTRICAL NETWORKS

SINA Y. CALISKAN AND PAULO TABUADA

Abstract. Kron reduction is used to simplify the analysis of multi-machine power systems under certain steady state assumptions that underly the usage of phasors. In this paper we show how to perform Kron reduction for a class of electrical networks without steady state assumptions. The reduced models can thus be used to analyze the transient as well as the steady state behavior of these electrical networks.

1. Introduction

Multi-machine power networks are the interconnection of power generators and substations via three-phase transmission lines. We can think of a multi-machine power network as a collection of a large number of interconnected nodes modeling generators and loads. Depending on the models used to describe the generators and the loads, we have a set of algebraic, differential, or algebro-differential equations per node. When the number of nodes increases this set of equations quickly becomes intractable. Common practice in the power systems literature is to reduce this set of equations, through a process called Kron reduction [11, Sec. 9.3], that results in a simpler set of equations providing the same relationships between voltage and current at the generators' terminals. This reduction, however, is based on the use of *phasors* and it requires the current and voltage waveforms in each phase to be sinusoidal and with the same frequency. This assumption seems contradictory if we want to study the transient behavior of a power system during which the waveforms are *not* sinusoidal.

The contribution of this paper is to identify a class of electric networks for which Kron reduction can be performed in the time domain, *i.e.*, without resorting to phasors. The reduced models can then be used to study the transient as well as the steady state behavior of these electrical networks which can be used to describe, *e.g.*, short transmission lines.

A graph-theoretic discussion of Kron reduction can be found in [7]. Our results are based on the very same graph-theoretic constructions. The problem of Kron reduction can be understood as a system equivalence problem: when do two models - the original and the Kron reduced - describe the same terminal behavior? This problem was first solved for purely resistive circuits in [4] and then for RLC circuits in [6] by describing not only when two models are equivalent but also by describing all such equivalent models. In the context of Kron reduction we are interested in constructing the smallest model that describes the relationships between voltage

---

Key words and phrases. Electrical circuits, graph theoretical models, linear/nonlinear models, identification and model reduction.

and current at the generators' terminals. This problem was solved for purely resistive, purely inductive and purely capacitive circuits in [1, 2] and for a class of RL circuits called *homogeneous* RL networks in [3]. This paper generalizes the results in [3] by describing a larger class of electrical networks for which Kron can be performed in the time domain.

2. Notation and Definitions

Let $\mathbb{N}$ be the set of natural numbers, $\mathbb{R}$ be the set of real numbers, $\mathbb{R}_+$ be the set of all strictly positive real numbers and $\mathbb{R}_{+0} = \mathbb{R}_+ \cup \{0\}$. For any $n \in \mathbb{N}$, the set $\bar{n}$ is defined as $\bar{n} = \{1, \dots, n\}$. The cardinality of the set S is denoted by $|S|$. We also use $|x|$ to denote the absolute value of $x \in \mathbb{R}$. The set of all $n \times m$ matrices with real elements is denoted by $\mathbb{R}^{n\times m}$. The element of $\mathbb{R}^n$ with all entries equal to 0 is denoted by $\mathbf{0}_n$. We also use $\mathbf{0}_n$ to denote the zero map $\mathbf{0}_n : \mathbb{R} \to \mathbb{R}^n$, which maps every real number to $\mathbf{0}_n \in \mathbb{R}^n$. For any matrix $M \in \mathbb{R}^{n\times m}$, we denote the element located in the i^{th} row and the j^{th} column as M_{ij}. The absolute value $|M|$ of the matrix $M \in \mathbb{R}^{n\times m}$ is the matrix of same dimension which is defined as $|M|_{ij} = |M_{ij}|$. For any set of vectors $S = \{v_1, \dots, v_n\}$, $\mathbf{span}\, S$ is the vector space spanned by the elements of S. For any vector space V, $\mathbf{dim}\, V$ denotes the dimension of V. The kernel and the image of a map f are denoted by $\mathbf{ker}\, f$ and $\mathbf{im}\, f$. The set of all smooth functions with domain A and codomain B is denoted by $\mathcal{C}^\infty(A, B)$.

We follow [8] for the definitions related with graphs. A *graph* $\mathcal{G} = (\mathcal{V}, \mathcal{E})$ is a two-tuple with finite set of vertices $\mathcal{V}$ and finite set of edges $\mathcal{E} \subseteq \mathcal{V} \times \mathcal{V}$. If the edges have no sense of direction, the graph is called an *undirected graph.* In directed graphs, $(x, y) \in \mathcal{E}$ implies that nodes x and y are connected via an edge with tail vertex x and head vertex y. Let $v = |\mathcal{V}|$ and $e = |\mathcal{E}|$. Without loss of generality, we will assume $\mathcal{V} = \bar{v}$ for the rest of the paper. Any graph $\mathcal{G}$ is completely represented by a $v \times e$ matrix called *incidence matrix* B. The rows of the incidence matrix represent the vertices and the columns represent the edges. In directed graphs, every edge $e_k = (i, j)$, $k \in \bar{e}$ is encoded in the incidence matrix by setting $B_{ik} = -1$ and $B_{jk} = 1$ and $B_{xk} = 0$ for all $x \in \bar{v}\backslash\{i, j\}$. The set of adjacent vertices $\mathcal{A}$ is defined as $\mathcal{A} = \{(x, y) \in \mathcal{V} \times \mathcal{V} \ : \ (x, y) \in \mathcal{E} \text{ or } (y, x) \in \mathcal{E}\}$. A *path* of length ℓ from vertex i to vertex j is the subset of vertices $\{r_0, \dots, r_\ell\}$ such that $r_0 = i$, $r_\ell = j$, and $(r_{k-1}, r_k) \in \mathcal{A}$ for all $k \in \bar{\ell}$. The careful reader may notice that we are allowing to traverse edges in both directions in directed graphs. A graph is called a *connected graph* if for every $i, j \in \mathcal{V}$, $i \neq j$, there exists a path from i to j. Let $\mathcal{V}_b$ be a nonempty subset of $\mathcal{V}$. Then the matrix B_b is the matrix that is obtained by collecting the rows of B that correspond to a vertex in the set $\mathcal{V}_b$. A *cycle* of a graph is a connected subgraph in which every vertex has exactly two neighbors. For the rest of the paper, we will assume that every graph is connected.

We will need the following lemma, which is a slight modification of Lemma 2.1 in [7] and Theorem 3.1 in [2], to prove our main result. The first part of the lemma can be proved using similar arguments to the arguments used in [7] and following observation. For any directed, connected graph $\mathcal{G} = (\mathcal{V}, \mathcal{E})$, we can construct an undirected, connected graph $\hat{\mathcal{G}} = (\mathcal{V}, \hat{\mathcal{E}})$ by removing the directions of the edges. This can be achieved by obtaining the incidence matrix of the undirected graph $\hat{B}$ from the incidence matrix of the directed graph B by $\hat{B} = |B|$. Then we have

$|BWB^T| = |\hat{B}W\hat{B}^T|$ for any diagonal matrix W with strictly positive real diagonal elements.

Lemma 2.1 (Lemma 2.1 in [7], Theorem 3.1 in [2]). *Let $\mathcal{G} = (\mathcal{V}, \mathcal{E})$ be a directed, connected graph with the proper, nontrivial subsets $\mathcal{V}_i \subset \mathcal{V}$ and $\mathcal{V}_b = \mathcal{V} \backslash \mathcal{V}_i \subset \mathcal{V}$.*

1. *The matrix $B_i W B_i^T$ is invertible for any diagonal matrix $W \in \mathbb{R}^{e \times e}$ with strictly positive diagonal elements.*
2. *There exist a graph $\hat{\mathcal{G}} = (\mathcal{V}_b, \hat{\mathcal{E}})$ with incidence matrix $\hat{B}_b \in \{-1, 0, 1\}^{|\mathcal{V}_b| \times |\hat{\mathcal{E}}|}$ and a diagonal matrix $W_r \in \mathbb{R}_+^{|\hat{\mathcal{E}}| \times |\hat{\mathcal{E}}|}$ such that*

$$\hat{B}_b W_r \hat{B}_b^T = B_b W B_b^T - B_b W B_i^T (B_i W B_i^T)^{-1} B_i W B_b^T.$$

3. Kirchoff's Laws on Graphs

We review Kirchoff's Current Law (KCL) and Kirchoff's Voltage Law (KVL) on abstract graphs, which were introduced in [1, 2]. Let $\mathbb{R}^S$ be the vector space of all functions from S to the field of real numbers $\mathbb{R}$. The space of trajectories of currents entering into nodes is denoted by Λ_0, and it is defined as $\Lambda_0 = \mathcal{C}^\infty(\mathbb{R}, \mathbb{R}^{\mathcal{V}})$. We can identify $\mathbb{R}^{\mathcal{V}}$ with the vector space $\mathbb{R}^v$. Let $(\mathbb{R}^v)^*$ be the dual space of $\mathbb{R}^v$. The dual space of Λ_0 is denoted by Λ^0. We can interpret $\Lambda^0 = \mathcal{C}^\infty(\mathbb{R}, (\mathbb{R}^v)^*)$ as the space of trajectories of voltages on the nodes. Similarly, the space of trajectories of currents flowing through the edges is denoted by Λ_1, and it is defined as $\Lambda_1 = \mathcal{C}^\infty(\mathbb{R}, \mathbb{R}^{\mathcal{E}})$. We can identify $\mathbb{R}^{\mathcal{E}}$ with the vector space $\mathbb{R}^e$. The dual space of Λ_1 is $\Lambda^1 = \mathcal{C}^\infty(\mathbb{R}, (\mathbb{R}^e)^*)$, which can be interpreted as the space of trajectories of voltages across the edges. We can think of the incidence matrix B of graph $\mathcal{G}$ as the matrix representation of the linear map

$$B \ : \ \mathbb{R}^e \to \mathbb{R}^v. \tag{3.1}$$

Using the standard inner product in Euclidean spaces as the duality product, the dual map of (3.1) can be thought of as a linear map with matrix representation B^T. The linear map (3.1) can be extended to the map $\bar{B} \ : \ \Lambda_1 \to \Lambda_0$ defined by $(\bar{B} \circ f_1)(t) = B \circ f_1(t)$ for every $f_1 \in \Lambda_1$ and every $t \in \mathbb{R}$. Similarly, we can define the dual map $\bar{B^T} \ : \ \Lambda^0 \to \Lambda^1$ as $(\bar{B^T} \circ g^0)(t) = B^T \circ g^0(t)$ for every $g^0 \in \Lambda^0$ and every $t \in \mathbb{R}$. For the graph $\mathcal{G} = (\mathcal{V}, \mathcal{E})$, let $\{\mathcal{V}_b, \mathcal{V}_i\}$ be the partition of its set of vertices $\mathcal{V}$. In other words, $\mathcal{V} = \mathcal{V}_b \cup \mathcal{V}_i$ and $\mathcal{V}_b \cap \mathcal{V}_i = \emptyset$. We call the elements of $\mathcal{V}_b$ *boundary vertices* and the elements of $\mathcal{V}_i$ *internal vertices*. A graph $\mathcal{G}$ with at least one boundary vertex is called an *open graph* [1]. The partition $\{\mathcal{V}_b, \mathcal{V}_i\}$ of $\mathcal{V}$ leads to a decomposition of the incidence matrix B. Explicitly, the incidence matrix can be decomposed as $B = \begin{bmatrix} B_i \\ B_b \end{bmatrix}$. In this decomposition, B_b contains the rows of the incidence matrix that correspond to boundary vertices, and B_i contains the rows of the incidence matrix that correspond to internal vertices. The decomposition of B into B_b and B_i induces the decomposition of the vector space Λ_0 into Λ_{0b} and Λ_{0i}. Similarly, the dual space Λ^0 can be decomposed into Λ^{0b} and Λ^{0i}. We can define the linear maps $\bar{B}_b \ : \ \Lambda_1 \to \Lambda_{0b}$, $\bar{B}_i \ : \ \Lambda_1 \to \Lambda_{0i}$ and their dual maps as before.

Kirchoff's Current Law states that the sum of currents entering into a node at any time is zero. For the vector of trajectories of currents flowing across the edges $I_1 \in \Lambda_1$, $\bar{B}I_1$ represents the sum of the trajectories of currents entering into vertices. If the vertex is an internal vertex, this sum is zero. This can be stated as $\bar{B}_i I_1 = \mathbf{0}_{|V_i|}$. Since we can inject currents to the boundary vertices, the sum of the currents entering into a boundary node is equal to the injected current. This can be stated as $\bar{B}_b I_1 = I_{0b}$. Therefore, an open graph $\mathcal{G} = (\mathcal{V}, \mathcal{E})$ with the set of boundary vertices $\mathcal{V}_b$ satisfies KCL for $(I_{0b}, I_1) \in \Lambda_{0b} \times \Lambda_1$ if

$$\begin{bmatrix} \mathbf{0}_{|\mathcal{V}_i|} \\ I_{0b} \end{bmatrix} = \begin{bmatrix} \bar{B}_i \\ \bar{B}_b \end{bmatrix} I_1. \tag{3.2}$$

Kirchoff's Voltage Law states that the sum of voltages along a cycle is zero. This implies that for $V^1 \in \Lambda^1$, $V^1(t)$ is orthogonal to the cycle space of the graph for all $t \in \mathbb{R}$, where orthogonality is understood with respect to standard Euclidean inner product. The cycle space of a graph $\mathcal{G}$ with incidence matrix B is $\mathbf{ker}\, B$, where B is the linear map given by (3.1). Since $(\mathbf{ker}\, B)^* \cong (\mathbf{ker}\, B)^\perp \cong \mathbf{im}\, B^T$, KVL can be stated as $V^1(t) \in \mathbf{im}\, B^T$ for all $t \in \mathbb{R}$. In other words, there exists a potential $\psi^0 \in \Lambda^0$ such that $V^1(t) = B^T \psi^0(t)$ for all $t \in \mathbb{R}$. Therefore KVL can be stated as follows. There exists a potential $\psi^0 \in \Lambda^0$ such that

$$V^1 = \bar{B^T} \psi^0 = \bar{B_b^T} \psi^{0b} + \bar{B_i^T} \psi^{0i}. \tag{3.3}$$

For the rest of the paper, we will abuse notation and denote $\bar{B}$, $\bar{B}_i$, $\bar{B}_b$ by B, B_i, B_b, respectively.

4. Main Result

Assume that we have a network of electrical components. Each electrical component has two terminals. The constitutive relation of the electrical component is a relation between the current flowing through the electrical component and the voltage across its terminals. We consider electrical components with constitutive relations given by

$$\sum_{i=0}^{\nu} p_{ki} \frac{d^i}{dt^i} I_{1,k} = \sum_{i=0}^{\nu} q_{ki} \frac{d^i}{dt^i} V_k^1. \tag{4.1}$$

where $p_{ki}, q_{ki} \in \mathbb{R}_{+0}$, $I_{1,k}$ is the current flowing through the electrical component k and V_k^1 is the voltage across the terminals of the electrical component k. The *coefficient vectors* of (4.1) are defined as $p_k = (p_{k0}, \ldots, p_{k\nu}) \in \mathbb{R}_{+0}^{\nu+1}$ and $q_k = (q_{k0}, \ldots, q_{k\nu}) \in \mathbb{R}_{+0}^{\nu+1}$. The *coefficient matrices* are defined as $P = [p_1 \mid \ldots \mid p_e]$ and $Q = [q_1 \mid \ldots \mid q_e]$.

The constitutive relation for a linear ideal resistor is given by $rI_{1,k} = V_k^1$ and can be described by (4.1) if we take $\nu = 0$ and $\frac{p_{k0}}{q_{k0}} = r$. Similarly, the constitutive relations for inductors and capacitors, $\ell \dot{I}_{1,k} = V_k^1$ and $I_{1,k} = c\dot{V}_k^1$, are described by (4.1) when we set $\nu = 1$, $p_{k0} = 0$, $p_{k1} = \ell$, $q_{k0} = 0$, $q_{k1} = 1$, and $\nu = 1$, $p_{k0} = 0$, $p_{k1} = 1$, $q_{k0} = 0$, $q_{k1} = c$, respectively.

The constant upper bound $\nu \in \mathbb{N}$ in (4.1) is the same for every electrical component. In other words, the highest degree of differentiation in (4.1), which is a measure of the complexity of the electrical component, is independent of the electrical component. We can think of an electrical network as a directed graph in which each edge in the graph represents an electrical component. In this framework, electrical components relate the space of trajectories of currents flowing through the edges Λ_1 and its dual space, the space of trajectories of voltages across the edges Λ^1. In other words, for the directed graph $\mathcal{G}$, $(I_1, V^1) \in \Lambda_1 \times \Lambda^1$ satisfies the constitutive relations (4.1) if for every edge $e_k \in \mathcal{E}$, the relationship between $I_{1,k}$ and V_k^1 is given by (4.1), where $I_{1,k}$ is the k^{th} element of I_1 and V_k^1 is the k^{th} element of V^1. For every edge $e_k \in \mathcal{E}$, the coefficient vectors of (4.1) are p_k and q_k. For the rest of the paper, we will assume that $p_k \neq \mathbf{0}_{\nu+1}$ and $q_k \neq \mathbf{0}_{\nu+1}$ unless otherwise stated.

Definition 4.1. A *generalized electrical network* is a five-tuple $\mathcal{N} = (\mathcal{G}, \mathcal{V}_b, \nu, P, Q)$. It consists of an open directed graph $\mathcal{G} = (\mathcal{V}, \mathcal{E})$ with boundary vertices $\mathcal{V}_b$ on which KCL (3.2), KVL (3.3), and constitutive relations (4.1) are satisfied; ν is the constant in (4.1), and $P, Q \in \mathbb{R}^{(\nu+1)\times e}$ are the coefficient matrices.

We adapt the notion of terminal behavior, which was introduced in [4, 6], to our framework.

Definition 4.2. The terminal behavior $\mathcal{B}_{\mathcal{N}} \subset \Lambda_b^0 \times \Lambda_{0b}$ of a generalized electrical network $\mathcal{N} = (\mathcal{G}, \mathcal{V}_b, \nu, P, Q)$ is the relation defined by: $(\psi^{0b}, I_{0b}) \in \mathcal{B}_{\mathcal{N}}$ iff there exists a $\psi^{0i} \in \Lambda^{0i}$ such that $\psi^0 = (\psi^{0b}, \psi^{0i}) \in \Lambda^0$ and $I_0 = (I_{0b}, \mathbf{0}_{|\mathcal{V}_e|}) \in \Lambda_0$ satisfy KCL (3.2), KVL (3.3) and constitutive relations (4.1) on $\mathcal{G}$.

The problem addressed in this note is:

Problem 4.3 (Kron Reduction [7])**.** Given a generalized electrical network $\mathcal{N} = (\mathcal{G}, \mathcal{V}_b, \nu, P, Q)$, when can we construct another generalized electrical network $\hat{\mathcal{N}} = (\hat{\mathcal{G}}, \mathcal{V}_b, \nu, \hat{P}, \hat{Q})$ with $\hat{\mathcal{G}} = (\mathcal{V}_b, \hat{\mathcal{E}})$ and $\mathcal{B}_{\mathcal{N}} = \mathcal{B}_{\hat{\mathcal{N}}}$?

Note that every node in the graph $\hat{\mathcal{G}}$ is a boundary vertex. Therefore Problem 4.3 is equivalent to eliminating all the internal vertices of the generalized electrical network $\mathcal{N}$ without changing the terminal behavior and the complexity of the constitutive relations. Now, we can state our main theorem.

Theorem 4.4. *Problem 4.3 is solvable for the generalized electrical network* $\mathcal{N} = (\mathcal{G}, \mathcal{V}_b, \nu, P, Q)$ *if we have*

$$\mathbf{dim}\ \mathbf{span}\{p_1, \ldots, p_e\} = \mathbf{dim}\ \mathbf{span}\{q_1, \ldots, q_e\} = 1, \tag{4.2}$$

where p_i*,* q_i *are the coefficient vectors of (4.1) for edge* $e_i \in \mathcal{E}$*, where* $i \in \{1, \ldots, e\}$*.*

Proof. Assume that $\mathcal{N} = (\mathcal{G}, \mathcal{V}_b, \nu, P, Q)$ is a generalized electrical network satisfying (4.2). Condition (4.2) states that the vector space $\mathbf{span}\{p_1, \ldots, p_e\}$ has dimension one. This implies that the basis for this vector space consists of a single vector $\tilde{p} = (\tilde{p}_1, \ldots, \tilde{p}_e) \neq \mathbf{0}_{\nu+1}$. Thus for every $k \in \bar{e}$, there exists a constant λ_k such that $p_k = \lambda_k \tilde{p}$. Since every element of p_k is nonnegative for all $k \in \bar{e}$, we can assume without loss of generality that every element of $\tilde{p}$ is nonnegative. Hence, we can assume $\lambda_k \geq 0$ for all $k \in \bar{e}$. Similarly, the basis for the vector space $\mathbf{span}\{q_1, \ldots, q_e\}$ consists of a single vector $\tilde{q} = (\tilde{q}_1, \ldots, \tilde{q}_e) \neq \mathbf{0}_{\nu+1}$. From the same reasoning, we can assume $\gamma_k \geq 0$. Replacing p_k and q_k in (4.1) with $p_k = \lambda_k \tilde{p}$ and $q_k = \gamma_k \tilde{q}$, we obtain

$$\lambda_k \sum_{i=0}^{\nu} \tilde{p}_i \frac{d^i}{dt^i} I_{1,k} = \gamma_k \sum_{i=0}^{\nu} \tilde{q}_i \frac{d^i}{dt^i} V_k^1, \tag{4.3}$$

for every edge $e_k \in \mathcal{E}$. By assumption, we have $p_k \neq \mathbf{0}_{\nu+1}$ and $q_k \neq \mathbf{0}_{\nu+1}$. This implies that $\lambda_k \neq 0$ and $\gamma_k \neq 0$. Dividing (4.3) by λ_k for each $k \in \mathcal{E}$ and writing equation (4.3) for every edge $e_k \in \mathcal{E}$ in vector form, we obtain

$$\sum_{i=0}^{\nu} \tilde{p}_i \frac{d^i}{dt^i} I_1 = \Gamma \sum_{i=0}^{\nu} \tilde{q}_i \frac{d^i}{dt^i} V^1, \tag{4.4}$$

where $I_1 = (I_{1,1}, \ldots, I_{1,e})$, $V^1 = (V_1^1, \ldots, V_e^1)$ and Γ is a diagonal matrix with strictly positive diagonal elements. The matrix Γ is defined as $\Gamma_{kk} = \frac{\gamma_k}{\lambda_k}$ for all $k \in \bar{e}$. From KVL (3.3), we have $V^1 = B^T \psi^0$ for $\psi^0 \in \Lambda_0$. Replacing V^1 in (4.4), we obtain

$$\sum_{i=0}^{\nu} \tilde{p}_i \frac{d^i}{dt^i} I_1 = \Gamma \sum_{i=0}^{\nu} \tilde{q}_i \frac{d^i}{dt^i} B^T \psi^0 = \Gamma B^T \sum_{i=0}^{\nu} \tilde{q}_i \frac{d^i}{dt^i} \psi^0. \tag{4.5}$$

Multiplying both sides of the equation (4.5) by B results in

$$B \sum_{i=0}^{\nu} \tilde{p}_i \frac{d^i}{dt^i} I_1 = B \Gamma B^T \sum_{i=0}^{\nu} \tilde{q}_i \frac{d^i}{dt^i} \psi^0 \tag{4.6}$$

$$\Longleftrightarrow \sum_{i=0}^{\nu} \tilde{p}_i \frac{d^i}{dt^i} B I_1 = B \Gamma B^T \sum_{i=0}^{\nu} \tilde{q}_i \frac{d^i}{dt^i} \psi^0. \tag{4.7}$$

Using the previously defined partitioning of B into B_i and B_b, we obtain the following set of equations from (4.7)

$$\sum_{i=0}^{\nu} \tilde{p}_i \frac{d^i}{dt^i} B_b I_1 = B_b \Gamma B_i^T \sum_{i=0}^{\nu} \tilde{q}_i \frac{d^i}{dt^i} \psi^{0i} + B_b \Gamma B_b^T \sum_{i=0}^{\nu} \tilde{q}_i \frac{d^i}{dt^i} \psi^{0b} \tag{4.8}$$

$$\sum_{i=0}^{\nu} \tilde{p}_i \frac{d^i}{dt^i} B_i I_1 = B_i \Gamma B_i^T \sum_{i=0}^{\nu} \tilde{q}_i \frac{d^i}{dt^i} \psi^{0i} + B_i \Gamma B_b^T \sum_{i=0}^{\nu} \tilde{q}_i \frac{d^i}{dt^i} \psi^{0b}. \tag{4.9}$$

From KCL (3.2), we have $B_b I_1 = I_{0b}$ and $B_i I_1 = \mathbf{0}_{|\mathcal{V}_i|}$. Replacing $B_b I_1 = I_{0b}$ in (4.8) and $B_i I_1 = \mathbf{0}_{|\mathcal{V}_i|}$ in (4.9), we have

$$\sum_{i=0}^{\nu} \tilde{p}_i \frac{d^i}{dt^i} I_{0b} = B_b \Gamma B_i^T \sum_{i=0}^{\nu} \tilde{q}_i \frac{d^i}{dt^i} \psi^{0i} + B_b \Gamma B_b^T \sum_{i=0}^{\nu} \tilde{q}_i \frac{d^i}{dt^i} \psi^{0b} \tag{4.10}$$

$$\mathbf{0}_{|\mathcal{V}_i|} = B_i \Gamma B_i^T \sum_{i=0}^{\nu} \tilde{q}_i \frac{d^i}{dt^i} \psi^{0i} + B_i \Gamma B_b^T \sum_{i=0}^{\nu} \tilde{q}_i \frac{d^i}{dt^i} \psi^{0b}. \tag{4.11}$$

The matrix $B_i \Gamma B_i^T$ is invertible by Lemma 2.1. Therefore, we obtain from (4.11):

$$\sum_{i=0}^{\nu} \tilde{q}_i \frac{d^i}{dt^i} \psi^{0i} = -(B_i \Gamma B_i^T)^{-1} B_i \Gamma B_b^T \sum_{i=0}^{\nu} \tilde{q}_i \frac{d^i}{dt^i} \psi^{0b}. \tag{4.12}$$

Substituting $\sum_{i=0}^{\nu} \tilde{q}_i \frac{d^i}{dt^i} \psi^{0i}$ into (4.10), we obtain

$$\sum_{i=0}^{\nu} \tilde{p}_i \frac{d^i}{dt^i} I_{0b} = \left(B_b \Gamma B_b^T - B_b \Gamma B_i^T (B_i \Gamma B_i^T)^{-1} B_i \Gamma B_b^T \right) \sum_{i=0}^{\nu} \tilde{q}_i \frac{d^i}{dt^i} \psi^{0b}. \tag{4.13}$$

Smoothness of ψ^{0b} implies that the left hand side of (4.13) and the left hand side of (4.12) are continuous functions. Since $\tilde{p} \neq \mathbf{0}_{\nu+1}$ for any $\psi^{0b} \in \Lambda_b^0$, there exists a unique $I_{0b} \in \Lambda_{0b}$ that satisfies (4.13) and a unique ψ^{0i} that satisfies (4.12). Therefore, if I_{0b} and ψ_{0b} satisfy (4.13), then there exists a unique $\psi^{0i} \in \Lambda^{0i}$ such that $\psi^0 = (\psi^{0b}, \psi^{0i}) \in \Lambda^0$ and $I_0 = (I_{0b}, \mathbf{0}_{|\mathcal{V}_e}|) \in \Lambda_0$ satisfy KCL (3.2), KVL (3.3) and constitutive relations (4.1). Thus $(\psi_b, I_b) \in \mathcal{B}_{\mathcal{N}}$ iff I_{0b} and ψ_{0b} satisfy (4.13). We now want to construct a generalized electrical network $\hat{\mathcal{N}} = (\hat{\mathcal{G}}, \mathcal{V}_b, \nu, \hat{P}, \hat{Q})$ with $\hat{\mathcal{G}} = (\mathcal{V}_b, \hat{\mathcal{E}})$ and $\mathcal{B}_{\mathcal{N}} = \mathcal{B}_{\hat{\mathcal{N}}}$. From Lemma 2.1, there exists a graph $\hat{\mathcal{G}} = (\mathcal{V}_b, \hat{\mathcal{E}})$

with incidence matrix $\hat{B}$ and a diagonal matrix $\hat{\Gamma}$ with strictly positive diagonal elements such that

$$\hat{B}\hat{\Gamma}\hat{B}^T = B_b\Gamma B_b^T - B_b\Gamma B_i^T(B_i\Gamma B_i^T)^{-1}B_i\Gamma B_b^T. \tag{4.14}$$

We construct a generalized electrical network $\hat{\mathcal{N}}$ from the directed graph $\hat{\mathcal{G}}$ by defining the constitutive relations on $\hat{\mathcal{G}}$ as

$$\sum_{i=0}^{\nu}\tilde{p}_i\frac{d^i}{dt^i}\hat{I}_1 = \hat{\Gamma}\sum_{i=0}^{\nu}\tilde{q}_i\frac{d^i}{dt^i}\hat{V}^1. \tag{4.15}$$

Multiplying both sides of (4.15) by $\hat{B}$ and using (3.2), (3.3), (4.14); we obtain (4.13) from (4.15). Therefore we can construct a generalized electrical circuit $\hat{\mathcal{N}}$ that has the same terminal behavior as $\mathcal{N}$. ☐

We emphasize that the reduction process detailed in the proof of Theorem 4.4 is performed in the time domain and requires no steady state assumptions. We start with the generalized electrical network $\mathcal{N}$ that describes the relation between voltages and currents in the time domain and we constructed the Kron reduced generalized electrical network $\hat{\mathcal{N}}$ that has the same terminal behavior also described in the time domain by the constitutive relations (4.15).

The following example illustrates that Condition (4.2) in Theorem 4.4 is not necessary.

Example 4.5. Consider the generalized electrical network $\mathcal{N} = (\mathcal{G}, \mathcal{V}_b, \nu, P, Q)$ with $\mathcal{G}$ given below:



The constitutive relations for the edges $e_1 = (1,3)$ and $e_2 = (3,2)$ are $I_{1,1} = V_1^1$ and $\frac{d}{dt}I_{1,2} = V_2^1$, respectively. Note that $\nu = 1$. From KCL (3.2), we have $I_{0b,1} = I_{1,1}$, $I_{1,1} = -I_{1,2}$ and $I_{1,2} = -I_{0b,2}$. From KVL (3.3), we have $V_1^1 = \psi_3^0 - \psi_1^0$ and $V_2^1 = \psi_2^0 - \psi_3^0$. Replacing $I_{1,1}$, $I_{1,2}$, V_1^1 and V_2^1 in the constitutive relations, we obtain

$$\begin{aligned} I_{0b,1} = -I_{0b,2} &= \psi_3^0 - \psi_1^0, \\ \frac{d}{dt}I_{0b,1} = -\frac{d}{dt}I_{0b,2} &= \psi_3^0 - \psi_1^0. \end{aligned}$$

Combining these equations, we obtain

$$I_{0b,1} + \frac{d}{dt}I_{0b,1} = -I_{0b,2} - \frac{d}{dt}I_{0b,2} = \psi_2^0 - \psi_1^0. \tag{4.16}$$

There exists a ψ_3^0 such that $(\psi_1^0, \psi_2^0, \psi_3^0)$ and $(I_{0b,1}, I_{0b,2})$ satisfy KCL (3.2), KVL (3.3) and the constitutive relations if and only if (ψ_1^0, ψ_2^0) and $(I_{0b,1}, I_{0b,2})$ satisfy (4.16). Therefore $(\psi_1^0, \psi_2^0, I_{0b,1}, I_{0b,2}) \in \mathcal{B}_{\mathcal{N}}$ if and only if $(\psi_1^0, \psi_2^0, I_{0b,1}, I_{0b,2})$ satisfy (4.16). We now construct a generalized electrical network $\hat{\mathcal{N}} = (\hat{\mathcal{G}}, \mathcal{V}_b, 1, P, Q)$ such that $\mathcal{B}_{\hat{\mathcal{N}}} = \mathcal{B}_{\mathcal{N}}$. The directed graph $\hat{\mathcal{G}}$ is given below:



We pick the constitutive relation of the single edge in $\hat{\mathcal{N}}$ as

$$\hat{I}_{1,1} + \frac{d}{dt}\hat{I}_{1,1} = \hat{V}_1^1.$$

From KCL (3.2), we have $I_{0b,1} = -I_{0b,2} = \hat{I}_{1,1}$. From KVL (3.3), we have $\hat{V}_1^1 = \psi_2^0 - \psi_1^0$. Replacing $\hat{I}_{1,1}$ and $\hat{V}_1^1$ in the constitutive relations, we recover (4.16). Therefore $(\psi_1^0, \psi_2^0, I_{0b,1}, I_{0b,2}) \in \mathcal{B}_{\hat{\mathcal{N}}}$ if and only if $(\psi_1^0, \psi_2^0, I_{0b,1}, I_{0b,2})$ satisfy (4.16). This implies that $\mathcal{B}_{\mathcal{N}} = \mathcal{B}_{\hat{\mathcal{N}}}$. Hence Problem 4.3 is solvable. However $p_1 = (1, 0)$ and $p_2 = (0, 1)$. Therefore $\mathbf{dim}\,\mathbf{span}\,\{p_1, p_2\} = 2$ and Condition (4.2) does not hold.

If we pick the constitutive relations for the edges of $\mathcal{N}$ as $I_{1,1} = V_1^1$ and $I_{1,2} = \frac{d}{dt}V_2^1$, we can also verify that Problem 4.3 is solvable. In this case,

$$\mathbf{dim}\,\mathbf{span}\,\{q_1, q_2\} = 2$$

and Condition (4.2) does not hold. □

5. Application to RLC Circuits and Power Networks

Every RLC circuit can be modeled as a generalized electrical network by taking the electric components to be either resistors, inductors, or capacitors. When all the circuit elements are resistors we speak of a purely resistive circuit. Purely inductive and purely capacitive circuits can be defined similarly. It is shown in [2] that Problem 4.3 is solvable for purely resistive, inductive, or capacitive circuits. The same result can be obtained by the following corollary of Theorem 4.4.

Corollary 5.1. Problem 4.3 is solvable for the generalized electrical network $\mathcal{G}$ if $\mathcal{G}$ is a purely resistive, purely inductive or purely capacitive circuit.

Proof. We will prove the corollary for purely resistive circuits. The proofs for purely inductive and purely capacitive circuits are very similar. In a purely resistive circuit, $\boldsymbol{p}_i = (r_i, 0)$, and $\boldsymbol{q}_i = (1, 0)$, where $r_i \in \mathbb{R}_+^e$ is the resistance of the branch i. Hence, Condition (4.2) holds. The result follows from Theorem 4.4. □

A natural question to ask is what happens if we don't restrict ourselves to putting exactly one resistor, inductor or capacitor in each branch. One example of such circuits is *homogeneous* RL circuits [3]. Every branch of an homogeneous RL circuit is a series connection of a resistor and an inductor. The term homogeneous comes from the fact that for every two edge $e_i, e_j \in \mathcal{E}$ with resistance values r_i, r_j and inductor values ℓ_i, ℓ_j, we have $\frac{r_i}{r_j} = \frac{\ell_i}{\ell_j}$. In order to represent RL circuits, it is enough to set $\nu = 1$ and $(p_{i1}, p_{i2}, q_{i1}, q_{i2}) = (r_i, \ell_i, 1, 0)$ in (4.1) for all $i \in \bar{e}$, where r_i is the resistance value of the resistive component of branch i and ℓ_i is the inductance value of the inductive component of branch i. Note that homogeneity implies that there exists a constant $c \in \mathbb{R}$, $c > 0$ such that $\boldsymbol{p}_i = c\boldsymbol{p}_j$ for every $i, j \in \bar{e}$. Therefore Condition (4.2) holds and we can recover Theorem 4.4 in [3] as a corollary of Theorem 4.4. The concept of homogeneity can be generalized to RLC circuits. A *homogeneous* RLC circuit is an electrical circuit such that every branch is a series combination of a resistor, an inductor and a capacitor with the following condition: for every two edges $e_i, e_j \in \mathcal{E}$ with resistance values r_i, r_j, inductor values ℓ_i, ℓ_j, and capacitor values c_i, c_j; we have $\frac{r_i}{r_j} = \frac{\ell_i}{\ell_j} = \frac{c_i}{c_j}$. *Homogeneous RC* circuits and *homogeneous LC* circuits can be defined in a similar fashion. The previous discussion is summarized in the next result.

Corollary 5.2. Problem 4.3 is solvable for homogeneous RLC, RL, RC or LC circuits.

There are various transmission line models available in the literature [9], [10] [11]. The most accurate model is the distributed-parameter transmission line model, which is a set of partial differential equations for the voltages and currents. One can obtain a lumped circuit model of the distributed-parameter model if the waveforms are assumed to be sinusoidals. Medium length transmission lines can be approximated by π circuits, which are two-port RLC circuits. Another lumped model for the transmission line is the short line approximation. It is an approximation commonly used if the transmission line is relatively short (less than 60 kilometers [9], or 50 miles [11]). In the short line approximation the line is modeled as a series connection of a resistor and an inductor [11]. Hence every network of short transmission lines can be modeled as a generalized electrical network with $\nu = 1$, $\boldsymbol{p}_i = (r_i, \ell_i)$ and $\boldsymbol{q}_i = (1, 0)$ in (4.1), where r_i is the resistance value of the resistive component of branch i and ℓ_i is the inductance value of the inductive component of branch i. Moreover, if the network is a homogeneous RL circuit, it follows from Corollary 5.2 that we can perform Kron reduction. Different types of transmission line models are suitable for the analysis of different types of transients [13]. The short line approximation is used to analyze the electromechanical transients [12], [13]. One can argue that the assumption that allows us to use the short line approximation (sinusoidal voltages and currents) to study electromechanical transients also allows us to use phasors. However, in our framework we do not need to assume sinusoidal waveforms *per se*. As long as the short line approximation can accurately describe the transients in consideration, we can use the reduced model for transient analysis.

References

[1] A. J. Van der Schaft, B. M. Maschke, *Conservation Laws and Lumped System Dynamics*, Model-Based Control; Bridging Rigorous Theory and Advanced Technology, P.M.J. Van den Hof, C. Scherer, P. S. C. Heuberger, eds., Springer, ISBN 978-1-4419-0894-0, pp. 31–48, 2009.

[2] A. J. Van der Schaft, *Characterization and Partial Synthesis of the Behavior of Resistive Circuits at Their Terminals*, Systems & Control Letters, Vol. 59, pp. 423–428, 2010.

[3] S. Y. Caliskan, P. Tabuada, *Kron Reduction of Power Networks with Lossy and Dynamic Transmission Lines*, submitted to 51st IEEE Conference on Decision and Control, December 10-13, 2012, Maui, HI, USA.

[4] J. C. Willems, and E. I. Verriest, *The Behavior of Resistive Circuits*, Joint 48th IEEE Conference on Decision and Control and 28th Chinese Control Conference, December 16-18, 2009, Shanghai, P.R. China.

[5] J. W. Polderman, and J. C. Willems, *Introduction to the Mathematical Theory of System and Control: A Behavioral Approach*, ISBN 0-387-98266-3, Springer-Verlag, New York, 1998.

[6] E. I. Verriest, and J. C. Willems, *The Behavior of Linear Time Invariant RLC Circuits*, 49th IEEE Conference on Decision and Control, December 15-17, 2010, Atlanta, GA, USA.

[7] F. Dörfler, and F. Bullo, *Kron Reduction of Graphs with Applications to Electrical Networks*, Available in http://arxiv.org, arXiv:1102.2950v1[math.CO], 15. Feb. 2011.

[8] C. Godsil, and G. Royle, *Algebraic Graph Theory*, Graduate Texts in Mathematics, Vol. 207, Springer-Verlag, ISBN 0-387-95241-1, New York, 2001.

[9] M. V. Deshpande, *Electrical Power System Design*, ISBN 978-0-074515-75-4 ,Tata McGraw-Hill, 2001.

[10] P. W. Sauer, M. A. Pai, *Power System Dynamics and Stability*, ISBN 1-58874-673-9, Stipes Publishing L.L.C., Champaign, 1997.

[11] A. Bergen, V. Vittal, *Power System Analysis*, ISBN 0-13-691990-1, Prentice Hall, New Jersey, 2000.

[12] M. Pavella, P. G. Murthy, *Transient Stability of Power Systems: Theory and Practice*, ISBN 0-471-94213-8, John Wiley & Sons, West Sussex, England, 1994.

[13] H. W. Dommel, *Techniques for Analyzing Electromagnetic Transients*, IEEE Computer Applications in Power, Vol. 10, Issue 3, pp. 18–21, 1997.

Department of Electrical Engineering, University of California at Los Angeles, CA 90095-1594, United States
E-mail address: `caliskan@ee.ucla.edu`

Department of Electrical Engineering, University of California at Los Angeles, CA 90095-1594, United States
E-mail address: `tabuada@ee.ucla.edu`